

Description

The SURECOM SF-103 hand-held frequency counter is a more practical counter, even advanced features such as field strength measurement are incorporated. It is compact, truly pocket sized, test instrument designed for ease of use and dependable performance. Supplied as a complete with internal Li-ion battery pack, AC wall charger and antenna.



Introduction:

- The frequency meter capable of measuring the parameters of the frequency of the continuous carrier signal walkie-talkies, with signal strength indicator.
- it is the tool of choice for maintenance personnel ,test frequency and signal strength for wireless enthusiasts.
- This portable frequency counter is designed for counting continuous wave signal comes from Two-way Radio.
- There are easy ranges for you to choose. The ranges cover most of the frequency of the two-way radios you want to measure.
- Its four-button control is easy to use and its small size allows you to carry it anywhere you like.
- Work by TCXO(Temperature Compensate X'tal (crystal) Oscillator) ,In the range of -45 °C ~ 65 °C can reach $\pm 2 \sim \pm 4$ ppm accuracy
- This include very interesting frequency areas such as 2m HAM radio, all VHF and UHF
- DMR Radio signal e frequency counter.
- GUI Battery level

Feature & Specification:

Frequency range two select: 2MHz-200MHz / 27MHz -2800MHz

CTCSS/DCS Decoder

Frequency counter Digital mode for DMR radio

Work by TCXO(Temperature Compensate X'tal (crystal) Oscillator) 2~2.5ppm

Frequency Response time: 0.2-0.5sec.(CTCSS/CDCSS >0.5-1sec)

TFT Color Display: 240 x 320, LCD Dim level setting

Build-in Li-ion battery 3.7V 1500mAh

Dimensions: 70 x 30 x 90 mm

Net Weight: 113g

4 buttons control

Auto power off: 1-9 minutes

Charging battery LED indicator

Package include:

- 1 x SF-103 frequency counter
- 1 x Dual Band UHF / VHF antenna
- 1 x Belt Clip
- 1 x USB Charger with cable
- 1 x English Manual



JBM INSTRUMENTOS LTDA.
 Rua Araguaia, nº 69 – Boa Vista - Santa Rita do Sapucaí – MG - CEP: 37540-000 – Brazil
 Tel / Fax: +55 (35) 3471-3014 E-mail: vendas@jbminstrumentos.com.br - Web: www.jbminstrumentos.com.br